



PAD200-PD

PHOTOELECTRIC SMOKE SENSOR



LISTED



0328-0531

P/N See Chart

Features

- UL 268 7th Edition
- Low profile, less than 2 inches with the base
- Wide selectable sensitivity range of 1.0 to 3.7%/foot
- Sensor communicates sensitivity to control panel
- UL listed smoke calibration and sensitivity
- Optional locking tab to prevent unwanted removal
- Simple DIP switch address setting, no programming tool required
- LED alarm indicator
- UUKL Listed for Smoke Control

Specifications

Operating Voltage: 24 VDC

Detector Current Draw: 300 μ A

Alarm indicator: 1 LED

Alarm set-point range: 1.0 to 3.7 %/ft (3.6-12 %/m)

Installation temperature range: 32 to 120°F (0 to 49°C)

Operating relative humidity range: 0% to 93% (Non-condensing)

Start-up time: Max. 1 sec.

Maximum number of addresses per loop: 127

Maximum number of lighted indicators in alarm per loop: 30

Color: Eggshell White

Weight (no base): 101g (3.56 oz)

Height (no base): 1.35 in (34 mm)

Diameter (no base): 3.93 inches (100 mm)

Description

The Photoelectric Smoke Sensor is a listed Analog Addressable smoke sensor compatible with fire alarm control panels that utilize the Potter Addressable Device (PAD) protocol. The PAD200-PD is a low profile smoke sensor with a wide sensitivity range. The sensor and base (not included) are made of a durable plastic in an off-white color to blend in with the ceiling.

The PAD200-PD has a sensitivity range of 1.0 to 3.7 % per foot and is UL. The PAD200-PD features drift compensation and has built in dirty detector warning as well as. The PAD200-PD and the control panel communicate over a proven and robust digital communication path and the system analyzes the information at the particular device. The total polling speed is less than five (5) seconds, well under the UL requirements.

The sensor is compatible with any of the PAD series sensor bases and simply twists on. The PAD200-PD is addressed using DIP switches in the rear of the sensor and can be easily programmed in the field without special tools.

Setting the Address

Each addressable device on the SLC loop must have a unique address from 1 to 127 to function properly. The address is set using DIP switches.

Before connecting a device to the SLC loop, take the following precautions to prevent potential damage to SLC or device. Verify the following:

1. Power to the device is removed
2. Field wiring is correctly installed.
3. Field wiring has no open or short circuits.

Air Velocity Ratings

The PAD200-PD has an Open Area of Protection air velocity rating of 0 to 300 feet per minute.

The system has a maximum of 30 LEDs that can be turned on simultaneously. If the system already has 30 LEDs on, the PAD200-PD will operate even though the LED may not illuminate.



Operation

The PAD200-PD is an analog addressable sensor that uses one address on the Signaling Line Circuit (SLC) of a compatible fire alarm control panel. The unit communicates with the control panel as it is polled. The LEDs flash every time the unit is polled and they will flash at a fast rate if the unit is in an active status. The polling LED can be turned off if desired for less conspicuous operation.

The PAD200-PD with the PAD100-4DB or PAD100-6DB has a low profile of less than two (2) inches to blend into the surrounding environment. The sensor includes an insect screen to prevent foreign objects from reaching the chamber and that can be cleaned to restore operation of a dirty detector.

Sensor Sensitivity

The PAD200-PD and the compatible control panel work in tandem to keep the sensitivity consistent. As the sensor is installed over time, the sensor compensates for the dirt in the unit until it is out of range. At that time, the panel will indicate a dirty sensor. The sensor will then have to be cleaned or replaced.

The PAD200-PD can be programmed to provide a maintenance alert prior to reaching the dirty sensor level which will allow for intervention prior to the sensor going into trouble. This allows for sensor replacement or cleaning prior to a nuisance trouble occurs.

NOTE: As required by NFPA, do not install the sensors until all construction is complete and the work area has been thoroughly cleaned. If the sensors have been installed in a construction environment, they should be cleaned or replaced before the system is placed into service.

Spacing

The PAD200-PD is UL listed with a recommended maximum spacing of 30 feet. Refer to NFPA 72 for specific information regarding detector spacing, placement and special applications.

| Ordering Information | | |
|----------------------|--|-------|
| Model Number | Description | P/N |
| PAD200-PD | Photoelectric Smoke Sensor | 95977 |
| PAD100-6DB | 6" Addressable Detector Base | 97671 |
| PAD100-4DB | 4" Addressable Detector Base | 97672 |
| PAD100-IB | 6" base with an isolator module included | 97673 |
| PAD100-RB | 6" base with one Form-C relay contact. 2A @ 30VDC, 0.5A @ 125VAC | 97675 |
| PAD100-SB | 6" base with sounder module included. Sound pattern is provided from external source | 97674 |

Note: Approvals/Listings maintained by and manufactured by Potter Electric Signal Company.

The seller makes no warranties, express or implied, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose, except as expressly stated in the seller's sales contract or sales acknowledgment form. Every attempt is made to keep our product information up-to-date and accurate. All specific applications cannot be covered, nor can all requirements be anticipated. All specifications are subject to change without notice.



1102 Rucpich Drive
Millennium Park
Crown Point, IN 46307
TEL: (219) 663-1600 FAX: (219) 663-4562
e-mail: info@janusfiresystems.com
www.janusfiresystems.com