



FHA

ANALOG FIXED TEMPERATURE HEAT DETECTOR



P/N 99236

Features

- 135-185° Fahrenheit Heat Sensor
- Low Profile
- Reliable Detection Technology
- LEDs for 360° viewing
- Ambient Temperature Listing of 32°F to 150°F
- For JFS-A Series control panels or JFS-IP Series control panels using Nohmi protocol



Description

The Fixed Temperature Heat Sensor (FHA) is a listed Analog/Addressable fixed temperature heat sensor compatible with any fire alarm control panel that has the Potter/Nohmi protocol. The heat sensing portion utilizes a proven thermistor for accurate and reliable heat detection. The sensor and base (not included) are made of a durable plastic in an eggshell white (off white) to blend in with the ceiling.

The FHA is UL and cUL listed with a selectable fixed temperature point from 135° to 185° Fahrenheit. This broad range allows the installer to cover a wide variety of applications with a single unit.

The FHA has two LEDs that allow for 360° viewing. The sensor is compatible with any of the Potter/Nohmi bases and simply twists on. The FHA is addressed using the hand held programmer or the control panel addressing function.

The system has a maximum of 13 LEDs that can be turned on simultaneously. If the system already has 13 LEDs on, the FHA will operate even though the LED will not illuminate.

Spacing

The FHA spacing is dependent on the alarm set-point. The unit is listed from 135°F to 185°F. However as the temperature setting increases, the spacing decreases.

Detector Spacing	
Alarm Set-Point	FHA Spacing
135 to 170 °F (57 to 76 °C)	Max. 50 ft
171 to 185 °F (77 to 85 °C)	Max. 15 ft

Setting the Address

Each addressable module, smoke sensor, heat detector and combination sensor/detector must have the address set before connecting the device to the SLC loop. The address is set using the hand held device programmer or the addressing feature on the control panel.

Before connecting a device to the SLC loop, take the following precautions to prevent potential damage to SLC or device. Verify the following:

1. Power to the device is removed.
2. Field wiring is correctly installed.
3. Field wiring has no open or short circuits.

Document discrepancies and notify appropriate personnel.



Operation

The FHA is an analog/addressable sensor that uses one address on the Signaling Line Circuit (SLC) of a compatible fire alarm control panel. The unit communicates with the control panel as it is polled. The LEDs flash every time the unit is polled and they will latch steady if the unit is in an active status.

The FHA is a single sensor that may be used in a wide variety of applications for property protection. The FHA has a high ambient installation temperature and has been tested in these environments. The unit has a sleek design and low profile for pleasing aesthetics. The temperature sensor is protected within the mold of the unit to prevent accidental damage

Specifications			
Working voltage range	22.0 to 24.0 V	Start-up time	Max. 1 sec.
Standby current (*)	250 μ A	Maximum number of addresses per zone	127
Alarm indicator	2 LEDs	Maximum number of lighted indicators in alarm per zone	13
Alarm indicator current	1.2 mA DC	Color	Eggshell White
Alarm set-point range	135 to 185°F / 57 to 85°C	Weight (without base)	73g (2.57oz)
Installation temperature range	32 to 150°F / 0 to 66°C	Dimensions (without base)	Height: 1.50 in (38 mm)
Operating relative humidity range	0% to 93% (Non-condensing)		Diameter: 4.0 inches (99 mm)
		Approvals / Listings	UL, ULC, CSFM

Compatible Bases

All bases will mount on a single gang, double gang, octagon, 4" square or mud ring electrical box.

Ordering Information		
Model Number	Description	P/N
FHA	Analog Fixed Temperature Heat Detector	99236
AB-6	6" Standard Analog Base	99234
AIB	Analog Isolator Base	99233
ARB	Analog Relay Base	99231

Note: Approvals/Listings maintained by and manufactured by Potter Electric Signal Company.

The seller makes no warranties, express or implied, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose, except as expressly stated in the seller's sales contract or sales acknowledgment form. Every attempt is made to keep our product information up-to-date and accurate. All specific applications cannot be covered, nor can all requirements be anticipated. All specifications are subject to change without notice.



1102 Rupcich Drive
 Millennium Park
 Crown Point, IN 46307
 TEL: (219) 663-1600 FAX: (219) 663-4562
 e-mail: info@janusfiresystems.com
 www.janusfiresystems.com