



# PAD100-CD

## CARBON MONOXIDE DETECTOR



P/N See Chart

### Features

- Carbon Monoxide detection device compliant with UL 2075
- 8 year lifespan with built in end of life indication
- Low profile
- Walk Test mode allows for fast easy validation of sensor operation
- Reliable detection technology
- LED Alarm Indicator
- UUKL Listed for Smoke Control

### Specifications

Operating Voltage: 24 VDC  
 Detector Current Draw: 300  $\mu$ A  
 Alarm indicator: 1 LED  
 Alarm set-point range: 70 ppm, 150 ppm, 400 ppm  
 Installation temperature range: 32 to 120°F (0 to 49°C)  
 Operating relative humidity range: 0% to 93% (Non-condensing)  
 Start-up time: Max. 1 sec.  
 Maximum number of addresses per loop: 127  
 Maximum number of lighted indicators in alarm per loop: 30  
 Color: Eggshell White  
 Weight (no base): 92g (3.25oz)  
 Height (no base): 1.43 in (36mm)  
 Diameter (no base): 3.93 inches (100mm)

### Description

The PAD100-CD is an Analog Addressable carbon monoxide (CO) sensor compatible with any fire alarm control panel that has the Potter Addressable Device (PAD) protocol. The CO sensing portion utilizes a proven electrochemical sensor for accurate detection of CO gas for life safety applications. The sensor and base (not included) are made of a durable plastic in an off white to blend in with the ceiling.

The PAD100-CD is listed to comply with the requirements of UL 2075. The sensor and the control panel communicate over a proven and robust digital communication path and the system analyzes the information at the particular device. The total polling speed is less than five (5) seconds, well under the UL requirements.

The sensor is compatible with any of the PAD series sensor bases and simply twists on. The PAD100-CD is addressed using DIP switches in the rear of the sensor and can be easily programmed in the field without special tools.

### Setting the Address

Each addressable device on the SLC loop must have a unique address from 1 to 127 to function properly. The address is set using DIP switches.

Before connecting a device to the SLC loop, take the following precautions to prevent potential damage to SLC or device. Verify the following:

1. Power to the device is removed
2. Field wiring is correctly installed.
3. Field wiring has no open or short circuits.



## Operation

The PAD100-CD is an analog addressable sensor that uses one address on the Signaling Line Circuit (SLC) of a compatible fire alarm control panel.

The unit communicates with the control panel as it is polled. The LED flashes every time the unit is polled and they will flash at a fast rate if the unit is in an active status. The polling LED can be turned off if desired for less conspicuous operation.

The PAD100-CD with the PAD100-4DB or PAD100-6DB has a low profile of less than two (2) inches to blend into the surrounding environment.

## Detection Levels

The PAD100-CD will provide alarm reports at these required levels:

Alarm set-point

70 ppm for 2 hours

150 ppm for 30 min

400 ppm for 10 minutes

Ordering Information		
Model Number	Description	P/N
PAD100-CD	Carbon Monoxide Detector	97667
PAD100-6DB	6" Addressable Detector Base	97671
PAD100-4DB	4" Addressable Detector Base	97672
PAD100-IB	6" base with an isolator module included	97673
PAD100-RB	6" base with one Form-C relay contact. 2A @ 30VDC, 0.5A @ 125VAC	97675
PAD100-SB	6" base with sounder module included. Sound pattern is provided from external source	97674

*Note: Approvals/Listings maintained by and manufactured by Potter Electric Signal Company.*

The seller makes no warranties, express or implied, including, but not limited to, the implied warranties of merchantability and fitness for a particular purpose, except as expressly stated in the seller's sales contract or sales acknowledgment form. Every attempt is made to keep our product information up-to-date and accurate. All specific applications cannot be covered, nor can all requirements be anticipated. All specifications are subject to change without notice.



1102 Rupcich Drive  
 Millennium Park  
 Crown Point, IN 46307  
 TEL: (219) 663-1600 FAX: (219) 663-4562  
 e-mail: [info@janusfiresystems.com](mailto:info@janusfiresystems.com)  
[www.janusfiresystems.com](http://www.janusfiresystems.com)